

AresX™ Indoor Jamming System

Handheld Anti-Tracking Jammer GPS L1/L2/L3/L4/L5





AresX™ Handheld Anti-Tracking Jammer GPS L1/L2/L3/L4/ L5 is mainly to used for anti-tracking purpose. It has been widely applied in mobile vehicle tracking. VIP convoy, security service, military units, banks, secret service custom and so on.

Features & Advantages

Good cooling system with built-in fans and wind slots in two sides to ensure the device to work continuously.

With internal rechargeable battery, simple to be replaced.

Adapted with a Nylon case to be carried more user-friendly.

Total RJ output power is 2watt.

With car charger to be used in the vehicle directly.

Each band can work separately or simultaneously.

Charging while working.

SPECIFICATION

Frequency Range GPS L1: 1575.42Mhz GPS L2: 1227.6Mhz GPS L3: 1381.05 Mhz GPS L4: 1841.4Mhz GPS L5: 1176.45Mhz Total Power 2watt Power Supply AC:110/220 V/DC12V Net Weight 275g Size (without antennae) Built-In Battery 1800mAh, lasting around 1hr Colour
Total Power Power Supply AC:110/220 V/DC12V Net Weight Size (without antennae) Built-In Battery GPS L5: 1176.45Mhz AC:110/220 V/DC12V 113 * 60 * 31mm 1800mAh, lasting around 1hr
Total Power Power Supply AC:110/220 V/DC12V Net Weight Size (without antennae) Built-In Battery 2watt AC:110/220 V/DC12V 113 * 60 * 31mm 1800mAh, lasting around 1hr
Power Supply AC:110/220 V/DC12V Net Weight Size (without antennae) Built-In Battery AC:110/220 V/DC12V 113 * 60 * 31mm 1800mAh, lasting around 1hr
Net Weight275gSize (without antennae)113 * 60 * 31mmBuilt-In Battery1800mAh, lasting around 1hr
Size (without antennae) Built-In Battery 113 * 60 * 31mm 1800mAh, lasting around 1hr
Built-In Battery 1800mAh, lasting around 1hr
Colour
Cotodi
Operating Temperature -35°C ~ 80°C
Operating Humidity up to 80%